

XFP 1 Loop 32 Zone Addressable Fire Panel (XP95/Discovery protocol)

Part No. **XFP501/X**



Overview

C-TEC's XFP single loop 32 zone addressable fire alarm panel offers high performance at a very competitive price. LPCB certified to EN54 parts 2 & 4, it is supplied in durable metal enclosure, offers combined keypad or keyswitch entry to Access Levels 2 and 3 and is compatible with Apollo's XP95/Discovery protocol. Ideal for use in small stand-alone applications or in larger applications due to its ability to sit on network of up to 8 XFP master panels, it is one of Europe's best-selling addressable fire panels. Packed full of engineering features - please refer to the feature list below - the XFP501/X is also fully compatible with C-TEC's Hush Button fire alarm solution and its new range of EN54 certified addressable sounders and VADs.



More Information

```
[et_pb_section fb_built="1" _builder_version="4.16" custom_padding="0px||||false|false" global_colors_info="{ }"]
[et_pb_row _builder_version="4.16" background_size="initial" background_position="top_left" background_repeat="repeat" width="100%"
custom_padding="0px|0px|false|false" global_colors_info="{ }"]
[et_pb_column type="4_4" _builder_version="4.16" custom_padding="||||"
global_colors_info="{ }" custom_padding_hover="||||"]
[et_pb_wc_breadcrumb _builder_version="4.16"
global_colors_info="{ }" custom_padding_breadcrumb="[et_pb_wc_breadcrumb][et_pb_wc_cart_notice _builder_version="4.16"
global_colors_info="{ }"]
[et_pb_wc_cart_notice][et_pb_column][et_pb_row][et_pb_row _builder_version="4.16" background_size="initial"
background_position="top_left" background_repeat="repeat" width="100%" custom_padding="0px||||false|false" global_colors_info="{ }"
column_structure="1_2_1_2"]
[et_pb_column type="1_2" _builder_version="4.16" custom_padding="||||" global_colors_info="{ }"
custom_padding_hover="||||"]
[et_pb_wc_images _builder_version="4.16"
global_colors_info="{ }"]
[et_pb_wc_images][et_pb_column][et_pb_column type="1_2" _builder_version="4.16" custom_padding="||||"
global_colors_info="{ }" custom_padding_hover="||||"]
[et_pb_wc_title _builder_version="4.16" global_colors_info="{ }"]
[et_pb_wc_rating _builder_version="4.16" global_colors_info="{ }"]
[et_pb_wc_price _builder_version="4.16" global_colors_info="{ }"]
[et_pb_wc_price][et_pb_wc_description _builder_version="4.16"
global_colors_info="{ }"]
[et_pb_wc_description][et_pb_wc_add_to_cart _builder_version="4.16"
```

```
global_colors_info="{ }"[/et_pb_wc_add_to_cart][et_pb_wc_meta_builder_version="4.16"
global_colors_info="{ }"[/et_pb_wc_meta][et_pb_column][et_pb_row][et_pb_row_builder_version="4.16" background_size="initial"
background_position="top_left" background_repeat="repeat" width="100%" global_colors_info="{ }"[/et_pb_column type="4_4"
_builder_version="4.16" custom_padding="|||]" global_colors_info="{ }" custom_padding_hover="|||]"[/et_pb_wc_tabs_builder_version="4.16"
global_colors_info="{ }"[/et_pb_wc_tabs][et_pb_wc_upsells_builder_version="4.16"
global_colors_info="{ }"[/et_pb_wc_upsells][et_pb_wc_related_products_builder_version="4.16"
global_colors_info="{ }"[/et_pb_wc_related_products][et_pb_column][et_pb_row][et_pb_section]
```

Technical Specifications

Approvals/certifications	Certified to EN54-2 & 4 by the LPCB.
Protocol/compatibility	Apollo XP95/Discovery.
Mains supply	230V 50/60Hz.
Mains rated current	680mA maximum.
Internal power supply	27Vdc nominal.
Total output current limited to	3A @ 230Vac (Imax.A 250mA; Imin. 70mA).
Quiescent current	80mA (loop unloaded).
Max battery size and type	2 x 12V 7Ah VRLA connected in series.
No. of loop drivers	1.
Max. loop output current	500mA (25V min; 34V max).
Max. loop length	1KM.
Max. addressable devices per loop	126.
No. of conventional sounder circuits	2 (Max. length per circuit is 500m).
EOL resistor value	6800Ω 5% Tol. 0/25W (blue, grey, red, gold).
Max. sounder output current	400mA.
Auxiliary relays	3 x Programmable Relays (programmable from C&Es). 1 x Fault Relay (active when no faults are present). Volt free single pole changeover. Max. switch current 1A; Max. switch voltage 30Vdc.
Other outputs	24V Aux. Power (19.5V min, 28V max). Protected by a resettable fuse. Max. current 100mA.
Auxiliary inputs	2 x Programmable Inputs (programmable from C&Es). Connect to 0V to trigger, Max. input voltage 27V (non-latching).
PC connection	PC connection via RS232 moxex connector (supplied in XFP507 upload/download software kit); No printer connection available.
Indicators	2 line x 40 character backlit display; 32 Zonal LEDs, General Fire; Energised; Pre-Alarm; Remote Output Activated; Remote Output Disabled; Accessed; Disablement; Test; Silenced; General Fault; Syst
Connections	Fixed, largest acceptable conductor size 1mm ² .
Expansion connections	2-wire RS485 non-redundant network/repeater connection available via optional AFP711 network card. Max. 8 mains per network or 8 repeaters per non-networked main. Limit 1KM (main panel network) or
Product dimensions (mm)	410 W x 250 H x 80 D mm (base); 439 W x 274 H x 7 D mm (lid).
Construction & finish	Metal.
IP Rating	IP30.
Weight	4.5kg (no batteries).
Operating conditions/temperature	-5°C to +40°C. Max relative humidity: 95%.